



Thank you for purchasing our Westwood Drop Coin Timer; a lot of thought based on 30 year's experience of metering has gone into its design.

METERING MUST BE INSTALLED BY A QUALIFIED ELECTRICIAN.

PLASTIC CASE – to install: The top suspending screw should be screwed into a suitable firm surface leaving room to hook the top fitting of the wall bracket over the screw. Connect the supply as shown on the instructions below the terminals.

The Earth must be connected to the marked screw.

Hang the Timer on the top fixing screw and then secure in place with the final screw through the lower case from behind the cash tray.

METAL CASE – to install: The top suspending screw should be screwed into a suitable firm surface leaving room to get the case over; secure the case to the wall by two further screws behind the cash tray. Bring in the main supply and load cables through the most suitable "knock-out" and join them into the case with suitable grommets or flanges. Connect in accordance with the instructions attached near the terminal block.

The Earth must be connected to the marked screw.

PRIMARY POWER ISOLATION – A Double Pole Switch Fused Spur suitably fused for the load **MUST BE USED** to isolate the unit from the mains supply. On the basic Plastic or Metal case versions the use of a RCD (Residual Current Device) is left to the discretion of the fitting electrician upon the situation and kind of use expected.

With the Hair Dryer and Iron models, bearing in mind the opportunities for misuse, wear and vandalism a RCD must be fitted.

TO ALTER THE TIME SETTINGS: The instructions are attached inside the front cover on the Plastic Case version and on the Metal Case to the back of the case behind the cash tray. These instructions give the motor speed and the timer can be set to this speed, a half, a third, a quarter or one sixth thereof.

Should you encounter any difficulties please contact us and we will be pleased to advise.



01803 297179 | 01803 299488